

Clamp Meter



Safety Rating:

CAT II 600 V
CAT III 300 V

Specifications

Basic Functions	Range	Basic Accuracy
AC current (A)	40 A / 400 A	± (2.5% + 5)
	40 A / 600 A	
DC current (A)	40 A / 400 A	± (2% + 3)
	40 A / 600 A	
AC voltage (V)	4 V / 40 V / 400 V / 600 V	± (1% + 5)
DC voltage (V)	400 mV / 4 V / 40 V / 400 V / 600 V	± (0.8% + 1)
Resistance (Ω)	400 Ω / 4 KΩ / 40 KΩ / 400 KΩ / 4 MΩ / 40 MΩ	± (1% + 2)
Frequency (Hz)	10 Hz to 1 MHz	± (0.1% + 3)
	10 Hz to 10 MHz	
	10 MHz	
Duty cycle	-0.1% to 99.9%	-

Clamp Meter



Specifications

Basic Functions	Range	Basic Accuracy
Features		
Display count	-	3,999
Auto range	-	✓
Jaw capacity	-	28 mm
True RMS	-	✓
Duty cycle	0.1% to 99.9%	✓
Diode	-	✓
Auto power off	-	✓
Continuity buzzer	-	✓
Low battery indication	-	✓
Data hold	-	✓
Relative mode	-	✓
Setup	-	✓
Input impedance for DC V	Around 10 MΩ	✓

General Characteristics

Power	9 V battery (6F22)
LCD size	35.6 × 18 mm
Product colour	Orange and grey
Product size	208 × 76 × 30 mm
Standard accessories	Battery, test lead, carrying bag
Standard individual packing	Gift box, English manual
Standard quantity per carton	40 pieces
Standard carton measurement	540 × 495 × 335 mm (0.09 CBM per standard carton)

Part Number Table

Description	Part Number
Clamp Meter, TRMS	72-7226

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA™ is the registered trademark of the Group. © Premier Farnell plc 2011.

